



# ACE1160P17B

## P-Channel Enhancement Mode Power MOSFE

### Description

- High side switch for full bridge converter
- DC/DC converter for LCD display

### Features

- $V_{DS} = -60V$
- $I_D = -15.7A$
- $R_{DS(ON)}$  @  $V_{GS} = -10V$ , TYP  $72m\Omega$
- $R_{DS(ON)}$  @  $V_{GS} = -4.5V$ , TYP  $98m\Omega$

### Absolute Maximum Ratings

Parameter		Symbol	Max	Unit
Drain-Source Voltage		$V_{DSS}$	-60	V
Gate-Source Voltage		$V_{GSS}$	$\pm 20$	V
Drain Current (Continuous)*C	$T_A = 25^\circ C$	$I_D$	-15.7	A
	$T_A = 100^\circ C$		-10	
Drain Current (Pulsed)*B		$I_{DM}$	-63	A
Avalanche energy $L=0.1mH$		$E_{AS}$	28.8	mJ
Power Dissipation	$T_A = 25^\circ C$	$P_D$	42	W
Operating temperature / storage temperature		$T_J/T_{STG}$	-55~175	$^\circ C$

### Thermal Resistance Ratings

Parameter		Symbol	Maximum	Unit
Maximum Junction-to-Ambient*A	Steady State	$R_{thJA}$	50	$^\circ C/W$
Maximum Junction-to-Case (Drain)*A	Steady State	$R_{thJC}$	3	

A: The value of  $R_{thJA}$  is measured with the device mounted on  $1in^2$  FR-4 board with 2oz. Copper, in a still air environment with  $T_A = 25^\circ C$ . The value in any given application depends on the user's specific board design.

B: Repetitive rating, pulse width limited by junction temperature.

C: The current rating is based on the  $\leq 10s$  junction to ambient thermal resistance rating.




# ACE1160P17B

## P-Channel Enhancement Mode Power MOSFE

### Ordering information

ACE1160P17B XX + H





# ACE1160P17B

## P-Channel Enhancement Mode Power MOSFE

### Notes

ACE does not assume any responsibility for use as critical components in life support devices or systems without the express written approval of the president and general counsel of ACE Technology Co., LTD. As sued herein:

1. Life support devices or systems are devices or systems which, (a) are intended for surgical implant into the body, or (b) support or sustain life, and whose failure to perform when properly used in accordance with instructions for use provided in the labeling, can be reasonably expected to result in a significant injury to the user.
2. A critical component is any component of a life support device or system whose failure to perform can be reasonably expected to cause the failure of the life support device or system, or to affect its safety or effectiveness.

ACE Technology Co., LTD.  
<http://www.ace-ele.com/>